

SERVICE NOTE

EFFECT:

MONACO GP COCKPIT/ 50¢ per play

NUMBER: 001

Instructions for 50¢ per play modification for Monaco GP Cockpit:

Materials: 1 piggy-backed set of IC's: 7432/7474(bottom)

Procedure:

To convert your games to 50¢ per play, the enclosed piggy-backed IC's must be mounted to one of the Monaco logic boards. Proceed as follows:

- 1. Turn off game and remove game back piece.
- 2. Locate logic board #96577-P. This board is one of two logic boards mounted under the TV monitor. #96577-P is the lower of the two boards.
- 3. Locate IC33 on this board.
- 4. Mount the piggy-backed IC's on top of IC33. Be careful to match up pin 1 on all IC's.
 - 5. Carefully solder pins 7, 13, and 14 directly to pins 7, 13, and 14 on 1033.
 - 6. Turn the logic board over and carefully cut the etch leading from pin 7 of 1032.
 - 7. On top of the logic board, solder the blue wire from the piggy-backed chips to PIN 5 of IC125.
 - 8. Solder the RED wire to PIN 7 of IC32.
 - 9. This completes the modification. The game should now play for 50¢. If you have any questions about this mod, don't hesitate to call the Gremlin factory at (714)277-8700.

506 PER PLAY MOD. FOR MONACO

6

PICGY-BACK IC'S 7432 /7474 (BOTTOM)
7432 - CUT OFF PINS, 1, 2, 3, 4, 5, 6, 11, 12+

7474 - CUT OFE PINS 1,2,3,4,5,6,9,

PLACING 7432 ON TOP OPO 7474

JOIN THE 2 PON 2'S. + PIN 14'S.

4 7432-14 TO 7474-10

11 7432-9 TO 7474-8 TO 7474-12.

WARREN RED MARCH 34) TO

4 7432-10 TO 7474-11.

ATTACH RED WIRE (3" LONG) TO 7432-10 ATTACH BLUE WIRE (3" LONG) TO 7432-8